

PRODUCT INFORMATION SHEET

Actual status: 10.05.19



OUTPUT MODULE FOR SIGNALING DEVICES 1X

VdS-approval G 205030

OMS 3301

Part-No.: 30211



Intelligent Input/Output module for the Loop 3000 for the control of external optical and acoustic signaling devices with bidirectional isolator according to EN 54-17 and EN 54-18. Including one monitored fault input and one potential free relay output for signaling devices.

- Integrated automatic switch function of the output at „external signal line on/off“ signal by the fire control panel
- Connecting module with one freely programmable fault input and one output for the connection of signalling devices
- Programming of different switching variants of input and output also with time control
- Monitoring of the operating status via Loop 3000
- Independent programming of input and output
- Automatic and manual addressing on Loop 3000
- Integrated isolator and T-branch option
- Functions completely integrated via Loop 3000-protocol
- Multicolour LED for alarm (red) and fault (yellow)
- Robust wall mounted housing according with IP 54

Technical Data

| | |
|------------------------|---|
| Supply Voltage | 15 V to 32 V DC on 2-wire bus (max. 34 V DC) |
| Quiescent Current | 460 μ A |
| Alarm Current | 460 μ A; 5 mA with activated LED |
| Output | 1 relay, 1 switchover contact 30 V DC/1 A |
| Protection class | IP 54 |
| Ambient temperature | -10°C to +60°C |
| Humidity | max. 95% |
| Dimensions (H x B x T) | 93 mm x 93 mm x 55 mm |
| Weight | appr. 185 g |
| Material | ABS |
| Colour | Housing white |
| Standards | EN 54-18, EN 54-17 |
| VDS-approval | G 205030 |
| System-approval | S 210001, S216001 |
| CE-CPD-Number | 0786-CPD-20460 |
| Remarks | Accessories: With UBW 3311 1A, part no. 33542, one monitored output can be realised |